

DIMRRIP

*See current catalogue for further detail



Knob Styles available include:

DIMRRIP

DIMRRIPKBBK

DIMRRIPKBMW

DIMRRIPKMBK

DIMRKBSN

DIMRKBSNSV

Cleaning Guide:

Spraying cleaning products on to electrical products is not recommended.

It is important to ensure that switches are turned off before cleaning.

Do not use any cleaning sprays - only wipe down with damp cloth or rub with dry cloth. (Do not use an abrasive cloth as it may scratch the plastic).

Do not use harsh chemical cleaners as these can break down the plastic and cause it to crack.



Dimpala Trailing Edge Dimmer Ripple Tone Rejection for Flicker Free Dimming

- Dimpala Eclipse Rotary Control Dimmer provides optimised dimming of LED lamps and drivers. This two-wire phase control [wall plate] rotary dimmer has a minimum load rating of 2W.
- Although optimised for LED lighting loads, this dimmer also provides excellent compatibility with other common lamp types such as incandescent lamps and 12V halogen (dichroic) lamps / transformers.
- Fits Australian wall switch plate apertures (For example, the Trader range, plus #HPM and *Clipsal ranges).
- Separately switched 2-wire design - no neutral wire connection required for wallplate retrofit installation.
- Minimum brightness typical 0%.
- "Soft-start" helps prolong lamp and driver life.
- Inherent immunity to installation wiring short circuit fault.
- Complies with all relevant Australian standards.
- Mechanical Minimum Brightness setting by adjusting knob position on pot shaft.
- NOT SUITABLE FOR FANS OR MOTORS.

Knob Style and Colours Available



DIMRRIPKB
Standard
Comes supplied
with dimmer

Specifications					
Nominal Live Voltage Amplitude Range		220-240Vac			
Line Voltage Frequency		50Hz Nominal (47 - 53Hz)			
Load Brightness Control Range		<1% to >95% (load dependent)			
Rated Load		Refer Compatible Loads			
Minimum Load		2W			

Compatible Load Types			
Load Symbol	Load Type	Maximum Load	Notes
	Dimmable LED Drivers	250W	Maximum permitted number of drivers is 250W divided by driver nameplate power rating
	Dimmable LED Lamps	250W	Due to variety of LED lamp designs, maximum number of LED lamps is further dependent on power-factor result when connected to dimmer.
	Electronic Transformers	300W	
	Standard Iron-core Transformers	250W	Due to variety of transformers designs, max LV lighting load is further dependent on transformer efficiency
	Toroidal iron-core transformers	250W	
	Incandescent	300W	
	Dimmable CFL's	150W	Due to the variety of CFL designs, the maximum number of dimmable CFL lamps is make/model dependent
M.3 (M)	Small Motor Load	N/A	

*HPM is a registered trademark of Legrand Aust. Pty. Ltd.

*Clipsal is a registered trademark of Schneider Electric (Australia) Pty. Ltd.

Certification Number:
GMA-515308

GSM Electrical (Australia) Pty Ltd
Level 2, 142-144 Fullarton Road, Rose Park SA 5067
P: 1300 301 838 F: 1300 301 778 E: service@gsmc.com.au
www.gsmc.com.au

